

<b>LMR BATTERY SPECIFICATIONS</b>	PART NUMBER
	<b>BPUKNB45</b>

COMPATIBLE RADIOS	Kenwood NX240, NX340, NX1000, NX1200, NX1300, TK2000, TK2200, TK2200L, TK2200LP, TK2207, TK2212L, TK2300VP, TK2307, TK2302VK, TK2312, TK2400VP, TK2402VK, TK3000, TK3200, TK3200L, TK3200LP, TK3207, TK3212L, TK3300UP, TK3302UK, TK3307, TK3313, TK3400UP, TK3402UK, TKD240V, TKD340U
REPLACES OEM BATTERY	KNB-45L
COMPATIBLE CHARGERS	Endura EC1-KW6, EC1M-KW6, EC2M-KW6-D, EC6M-KW6, EC12M-KW6-D / Kenwood KSC-35S, KSC-43 / USB compatible
USB CHARGING	Internal circuitry allows charging with 24" USB cable included / status LED indicates charging, charge complete, or fault
VOLTAGE	7.4V
CAPACITY / ENERGY	1900 mAh / 14.1 Wh
CHEMISTRY / CELL TYPE	Li-Ion / Panasonic UF103450P (Japanese)
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	>500
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes (not required for battery run time or cycle life)
PROTECTION TYPES	Short circuit / over-charge / over-discharge / over-temperature monitoring via external charge contact
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	